



3.00mW x 5.96mD x 2.10mH







For construction in non-cyclonic areas
Wind rating: N2 as per AS4055-2021.
If you require a higher wind rating please contact
us: admin@absco.com.au or 1800 029 701


NOTE: This shed can be upgraded to wind rating: C1 as per AS4055-2021 with the additional purchase of a Cyclone Kit.



DOWNLOAD OUR APP FOR ASSEMBLY VIDEOS



Model: 3060UTK



When laying concrete slab, ensure there is a rebated edge 25mm deep around the perimeter. This will help water egress from the base of the shed.

PLEASE LEAVE A REVIEW

Tell us about your experience!
Visit www.abscosheds.com.au/review



3.00mW x 5.96mD x 2.10mH

GENERAL INSTRUCTIONS

- Before commencing any assembly, read through these instructions in detail to gain a thorough understanding of assembly methods and associated details.
- Unpack the carton and carefully identify and check off all the parts against the parts described and illustrated on "COMPONENTS PACKING LIST" pages.
- Local authority approval must be obtained prior to construction of the shed. Once you have selected your site you will need to lodge a site plan to your local council.

SITE PREPARATION

- The site for the shed must be level. An uneven surface may result in misalignment of parts.
- The shed shall be erected on top of a reinforced concrete slab and anchored down appropriately illustrated on "FINAL CONSTRUCTION" page. If using a rebated slab ensure that all frame uprights are trimmed 25mm.

TOOLS REQUIRED



SAFETY NOTES

- Some parts may have sharp edges. It is advisable to wear gloves when handling these items and safety glasses if drilling holes. Sensible shoes are highly recommended.
- Do not erect your shed in windy conditions.
- It is highly recommended to erect the shed with two or more people.

RECOMMENDED











Absco Industries Assembly Instruction Manual Model: 3060UTK 29/11/2021



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

Check off all components.

	MAIN PACK CARTON (PACK 1 OF 3)								
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
1	STEEL SHEET 1915mm X 773mm	36L		2	STEEL SHEET 1725mm X 711mm	37A			
1	STEEL SHEET 2045mm X 773mm	38L		1	STEEL SHEET 1785mm X 731mm	32A			
16	STEEL SHEET 1546mm X 773mm	45A		1	STEEL SHEET 1785mm X 731mm	33A			
2	STEEL SHEET 1725mm X 773mm	25A		2	STEEL SHEET 1785mm X 329mm	39B			
1	STEEL SHEET 1725mm X 773mm	В		1	PEAK BRACE	15A			
1	GABLE L/H L=1475mm	16L		2	RIDGE BEAM L = 1521mm	97AL			
1	GABLE R/H L=1475mm	16R		2	RIDGE BEAM L = 1521mm	97AR			
1	FITTINGS & ACCESSO PACKET (SEE PG			3	RIDGE BEAM JOINER L: 450mm (17.7")	ZARSP			



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

FITTINGS & ACCESSORIES PACKET CONTENTS									
QTY	COMPONENT DESCRIPTION	PART No.	СНЕСК	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
3	DOOR STRAP L: 165mm	12A		18	CHANNEL JOINER L= 200mm (7.9")	CSJ			
2	CAP GABLE L: 170mm	14A		5	RIDGE PLATES	RBP			
1	RIDGE CAP JOINER	98A		4	JAMB L= 75mm	93B			
1	PSTKDBL DOUBLE DOOR FITTING	S PACK		1	PSTKSGL SINGLE DOOR FITTING	S PACK			
20	HEX HD TEK SCREW W/ NEO WASHER 10-16x16mm			1	ASSEMBLY INSTRUC MANUAL	CTION			
	PSTI	(DBL - D	OUBLE D	OOR F	FITTINGS PACK				
3	PADBOLT 115mm LONG	FASTO0	06	2	PADBOLT HASP	FAST00)7		
1	8G x 3/8 SELF TAPPING SCREWS x 220	PACK2	20	1	SCREW PACK 12	PACK1	2P		
1	3mm DRILL BIT	DRILL		1	PHILLIPS HEAD DRIVER BIT S2 PH2	FAST03	38		
		PAC	(12P - SC	REW P	ACK 12		 		
12	SBS43E POP RIVET	FAST00)9	12	3/16" x 1/2" COUNTERSUNK SCREW & NUT	FASTO0			
8	3/16 x 1/2 PAN HEAD SCREW	FASTOC)2	8	3/16 NYLOCK NUT	FAST00)3		
	PST	KSGL - S	INGLE D	OOR F	ITTINGS PACK				
1	PADBOLT 115mm LONG	FAST00	06	1	PADBOLT HASP	FASTO()7		
1	8G x 3/8 SELF TAPPING SCREWS x 220	PACK2	20	1	SCREW PACK 6	PACK	SP		
1	3mm DRILL BIT	DRILL		1	PHILLIPS HEAD DRIVER BIT \$2 PH2	FAST03	38		
		PAC	CK6P - SC	REW P	ACK 6				
6	SBS43E POP RIVET	FASTO0)9	6	3/16" x 1/2" COUNTERSUNK SCREW & NUT	FASTO0			



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

	MAIN PACK CARTON (PACK 2 OF 3)								
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
1	STEEL SHEET 1915mm X 773mm	36R		10	STEEL SHEET 1785mm X 773mm	31A			
1	STEEL SHEET 2045mm X 773mm	38R		1	PORTAL PACK (SEE BELOW)	PF			
3	STEEL SHEET 1785mm X 773mm	30A		1	3060UTK CHANNEL SET (SEE PGs 7&8)				
	PORTAL PACK CONTENTS (80mm X 40mm CHANNEL SECTIONS)								
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
4	CHANNEL L = 1482mm	C1482		4	CHANNEL L = 1704mm	C1704			
		PORTA	L FRAME	ACCE	ESSORIES				
4	4 KNEE PLATE 8 10mm DYNABOLTS								
4	APEX PL	.ATE		300	16mm TEK SCREWS				
4	MULTI PU BRACKET			80	45mm TEK SCREWS				



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

	MAIN PACK (PACK 2 OF 3) CHANNEL SET								
QTY	COMPONENT DESCRIPTION	PART No.	СНЕСК	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
3	CHANNEL L = 1496.5mm	55BL		3	CHANNEL L = 1496.5mm	55BR			
1	CHANNEL L = 1496.5mm	56AL		1	CHANNEL L = 1496.5mm	56AR			
1	CHANNEL L = 1496.5mm	56BL		1	CHANNEL L = 1496.5mm	56BR			
4	CHANNEL L = 1496.5mm	60AL		4	CHANNEL L = 1496.5mm	60AR			
1	CHANNEL L = 1496.5mm	77CL		1	CHANNEL L = 1496.5mm	77CR			
5	CHANNEL L = 1496.5mm	81AL		5	CHANNEL L = 1496.5mm	81AR			
3	CHANNEL L = 1496.5mm	81BL		3	CHANNEL L = 1496.5mm	81BR			



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

MAIN PACK (PACK 2 OF 3) CHANNEL SET (CONT.)								
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK	
3	CHANNEL WITH HINGES L = 1725mm	58A		3	JAMB L= 1785mm	89A		
2	CHANNEL L = 1725mm	58B		1	JAMB L= 1785mm	89B		
2	CHANNEL L = 773mm	58C		1	JAMB L= 1725mm	89C		
4	CHANNEL L = 1155mm	63A		1	JAMB L= 788mm	90B		
1	CHANNEL L = 788mm	79B		2	JAMB L= 1120mm	91A		
2	CHANNEL L = 329mm	81M		1	JAMB L= 1537mm	93L		
1	CHANNEL L = 1518mm	84L		1	JAMB L= 797mm	93R		
1	CHANNEL L = 1518mm	84R		4	LIP TRIM L= 1546mm	87A		



3.00mW x 5.96mD x 2.10mH

COMPONENT PACKING LIST

FRONT FRAME PACK (PACK 3 OF 3)									
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
2	CHANNEL L = 2300mm	C2300		8	CHANNEL L = 285mm	K0285			
2	CHANNEL L = 1820mm	N1820		2	CHANNEL L = 240mm	C0240			
2	€ Land South State CHANNEL L = 1785mm	C1785		2	CHANNEL L = 100mm	C0100			
2	€ Land State CHANNEL L = 1484mm	M1484							
QTY	COMPONENT DESCRIPTION	PART No.	CHECK	QTY	COMPONENT DESCRIPTION	PART No.	CHECK		
1	HAT= 2290mm	99A		1	SMALL TRIANGUL PLATE	AR			
4	HAT= 1350mm	99B		150	SELF DRILLING 16mm TEK SCREWS				
10	MULTI PU BRACKE			1	PHILLIPS HEAD DRIVER BIT				
6	ı	mm .BOLTS							



3.00mW x 5.96mD x 2.10mH

Guide on Splitting Sheets

- This product comes with a perforated sheet that is designed to be split into two smaller sheets.
- These sheets have sharp edges. Once separated please use appropriate foot and hand protection when handling.
- In order to split the sheet lay it on the ground and lift and fold one end until the perforations have cleanly snapped.
- Discard the middle piece as scrap when convenient. Fold the scrap piece in half two or three times and throw in garbage.









Fold first side of sheet until free

Fold middle section of sheet until free

Discard middle piece

	SPLITTING SHEET 39B								
QTY	COMPONENT DESCRIPTION	PART No.		QTY	COMPONENT DESCRIPTION	PART No.			
1	STEEL SHEET 1785mm X 773mm	39B	=	2	STEEL SHEET 1785mm X 329mm	39B			

Model: 3060UTK




3.00mW x 5.96mD x 2.10mH

SNAPTITE ASSEMBLY GUIDE

The Snaptite Assembly System locks end channels to all roof and wall sheets without the need for tools and fasteners.

To assemble each panel, the perimeter channels are secured to the top and bottom of each panel. Gently tap the channel over the SNAPTiTE lugs on the sheet, working along the sheet.

Each perimeter channel must finish flush with the edges of the sheets. Simply tap the channel along the sheets until each end is neatly flush. If you need to remove channels from the panels, slide it off from the side.





Channel locks the shed panel into position without the need for screws!

FASTENING SYMBOLS




Secure channel to sheeting by SNAPTiTE fastening method.



Join components together with one screw at this location only, as some channels have extra holes that are not required for this model of shed.



Do not join components together at this location yet, as the screws may obstruct further assembly of the other components.





4mm nut and bolt set. ◫

10 **Absco Industries** Assembly Instruction Manual Model: 3060UTK 29/11/2021 1.3



3.00mW x 5.96mD x 2.10mH

Guide on Joining Spliced Channels

The text marked on all parts must be shown on the same side as each other




Step 1. Position the channels and the CSJ joiner so the centre of the CSJ is in line with the end of each channel to be joiner together.




Step 2. Join the first channel to the CSJ by inserting the centre of the CSJ, on an angle, to the end of the channel where the JOIN>> text is marked.



Push down one side of the CSJ until you hear a 'click'.





Step 3. Join the second channel to the CSJ by positioning the << JOIN of the channel at the centre of the CSJ, on an angle. Push the CSJ into the channel until you hear a 'click'.



Finished Channel. The joined channels should now look like the picture with the CSJ positioned equally inside of the joined channels.

Drill out holes with 3mm drill bit in CSJ to match the holes in channel. Drilling of screws on the joined channels is being done after sheets are locked on the spliced channels.








3.00mW x 5.96mD x 2.10mH

PRE-ASSEMBLY OF SPLICED CHANNELS

Join together 36 x channel sections using 18 x channel joiners (Part CSJ)



1.3




3.00mW x 5.96mD x 2.10mH

Guide on Joining a Spliced Ridge Beam


Follow these three steps to assemble a ridge beam.



Step 1. Place two ridge beams as shown and push them together. Slide the cap of one under the other.



NOTE. There is a 50mm overlap of the ridge caps when the beams are in position.



Step 2. Use the ZARSP to connect at the centre of the two ridge beams. Be sure it is pushed in fully.



Step 3. Turn over the ridge beam. Measure 250mm from the middle along the centre of one ridge beam, mark spacings of 50mm. Fasten with a Tek screw at each marking.




Repeat to the other side of the ridge beam assembly.



Finished Spliced Ridge Beam

TIP: Predrilling each hole with the 3mm drill bit makes it easier to fasten.

Model: 3060UTK






Joined Ridge Beams

1.3



3.00mW x 5.96mD x 2.10mH


PRE-ASSEMBLY OF SPLICED RIDGE BEAM



1.3



3.00mW x 5.96mD x 2.10mH








3.00mW x 5.96mD x 2.10mH


OVERVIEW OF ROOF COMPONENTS





3.00mW x 5.96mD x 2.10mH


OVERVIEW OF WALL COMPONENTS





3.00mW x 5.96mD x 2.10mH

ROOF PANEL ASSEMBLY




18




3.00mW x 5.96mD x 2.10mH

SIDE PANEL ASSEMBLY










3.00mW x 5.96mD x 2.10mH

JOINING WALL AND ROOF PANELS

To make the total span we must now join sections of sheeting together for the roof and wall.



Refer to the panel construction section of this instruction set for further details and ensure that the assembled panels are not joined together with pre-punched holes incorrectly positioned.

The overall length of each panel is the same as the ridge beam.

It is not critical that the overall dimension is exact but try and make sure the length is within 5mm.


1.3




3.00mW x 5.96mD x 2.10mH

DOOR PANEL ASSEMBLY SINGLE DOOR


1 required.




Vertical door channels are installed in the opposite orientation compared to the horizontal door channels.






















3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL FRAME DETAILS




NOTE: If you have a slab with an edge rebate in your concrete slab, you will have to cut an amount off the bottom of the frame legs equal to the depth of the rebate.

Absco Industries Assembly Instruction Manual Model: 3060UTK 29/11/2021 1.3 26



3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL FRAME DETAILS







3.00mW x 5.96mD x 2.10mH


CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STFP 1

Draw pattern on the concrete in accordance with the dimensions detailed in the assembly instructions.










3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STEP 2.

Understand where components are to be positioned




Model: 3060UTK





3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STEP 3. Join rafter to column with knee plate









3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS


STEP 4.

Join both rafters using the apex plate


Step 4a



Step 4b



Step 4c






3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STEP 5. Secure ridge plate (RBP)









3.00mW x 5.96mD x 2.10mH

CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STEP 6. Secure multi purpose brackets








3.00mW x 5.96mD x 2.10mH


CENTRE PORTAL ASSEMBLY SUPPORT PHOTOS

STEP 7.

Turn frame over and repeat steps 4 and 5.







Step 7d






3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY

STEP 1 of 2






3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY

Absco Industries



NOTE: IF YOU HAVE AN EDGE REBATE IN YOUR CONCRETE SLAB, YOU WILL HAVE TO CUT AN AMOUNT OFF THE BOTTOM OF THE FRAME LEGS EQUAL TO THE DEPTH OF THE REBATE.





3.00mW x 5.96mD x 2.10mH


FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STFP 1

Draw pattern on the concrete in accordance with the dimensions detailed in the assembly instructions.










3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 2.

Understand where components are to be positioned.

Step 2



1.3

29/11/2021




3.00mW x 5.96mD x 2.10mH


FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 3.

Join C0100 to the bottom of the columns (C1785)









3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS


STEP 4.

Join rafter (M1484) to column (C1785)

Step 4a



Step 4b





3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS


STEP 5.

Join K0285 to C1785 & N1820.


Step 5a




Step 5b



Step 5c



Step 5d



Step 5e



Step 5f



Absco Industries

Assembly Instruction Manual

Model: 3060UTK

41




3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 6.


Fit mulitpurpose brackets.


Step 6a



Step 6b

Absco Industries





42


1.3



3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 7.



Step 7e






3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 8.

Join all sections together.

Step 8a



Step 8b




Step 8c



Step 8d



Step 8e





3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS


STEP 9.

Turn over frame and repeat steps 4 to 8.

Step 9a



Step 9b






3.00mW x 5.96mD x 2.10mH

FRONT FRAME ASSEMBLY SUPPORT PHOTOS

STEP 10.


Fully assembled front frame.





3.00mW x 5.96mD x 2.10mH


FRONT PANEL ASSEMBLY





3.00mW x 5.96mD x 2.10mH

PORTAL FRAME DETAILS




- Secure multipurpose brackets to uprights using self drilling screws
- Move frames into postion, mark and drill holes in slab using 10mm masonry drill bit
- Secure frames to slab with M10 dynabolts.

29/11/2021



3.00mW x 5.96mD x 2.10mH



Absco Industries



3.00mW x 5.96mD x 2.10mH

ROOF CONSTRUCTION

STEP 1.

Secure peak brace to ridge beam and roof panel with one screw at each end, see **A** below.

STEP 2.


Move the other roof panel into position and secure peak brace to ridge beam and roof panel with one screw at each end, see **B** below.

STEP 3.

Secure both roof panels to the walls with one screw in each corner first, followed by two screws adjacent to the portal frame as shown.

STEP 4.

Secure roof panels to the top chords of the portal frame using 45mm self drilling tek screws.





3.00mW x 5.96mD x 2.10mH

FINAL CONSTRUCTION

STEP 1.

Secure the roof panels to the wall panels as shown.

STFP 2.

Secure the roof panels to the internal frames with self drilling tek screws.

STFP 3.


Secure the portal frames to the ridge beam as detailed on the previous page.

STEP 4.

Bend the top and bottom flanges as shown, then hook the bottom flanges under the top channel and screw top to the ridge beam with two screws.

Location of 24 concrete anchors. Refer to section PORTAL FRAME for portal anchor locations.

ANCHORING OF SHED



Absco Industries

Drill a 10mm hole into the concrete.

Assembly Instruction Manual


29/11/2021

* Denotes hot dip galvanised finish

1.3



3.00mW x 5.96mD x 2.10mH





3.00mW x 5.96mD x 2.10mH

Absco Large Gable Roof Shed Notes

General

- 1.G This instruction manual shall be read in conjunction with other consultants drawings, specifications and written instructions provided by Absco and/or their representatives.
- 2.G The drawings provided herein are for installation and structural engineering purposes only. If discrepancies are discovered within the documentation provided, these shall be brought to the attention of Absco and written approvals obtained prior to commencing the affected section of work.
- 3.G If in doubt ask.
- 4.G Until approvals from the local authorities are obtained, commencement of construction from these drawings shall not commence.
- 5.G Unless varied by the project specification, all materials and workmanship shall be undertaken in accordance with the relevant Australian standards and the by-laws and ordinances of the relevant building authorities.
- 6.G All dimensions indicated in these drawings shall be verified on site by the installation contractor. Scaling of drawings shall not be undertaken.
- 7.G Prior to commencing works on site, the contractor shall verify the position of all services in the area to ensure that the construction does not interfere with any of those services.
- 8.G During installation on site the shed structures shall be maintained in a stable condition with no part becoming overstressed or permanently deformed.
- 9.G In circumstances where the shed has been installed in a manner which is inconsistent with the installation manual, structural certification shall be void.
- 10.G The structural components detailed within this installation manual have been designed for the following loads in accordance with AS/NZS1170 based on a Class 10a, Type 2 structure:
- Roof Live Load: 0.25 kPa uniformly distributed or 1.1 kN concentrated as per AS/NZS1170.1

Wind Load: Classification N2, Non-Cyclonic to AS4055 where Vu = 40 m/s, Vs = 26 m/s


Windward wall Cpe = 0.7


Leeward Wall Cp, e = -0.3 to -0.5 as applicable based on shed geometry

Side Wall Cp, e = -0.2 to -0.65 as applicable based on shed geometry

Roof Cp, e = -0.3 to -1.04 depending on wind direction







53



3.00mW x 5.96mD x 2.10mH

Absco Large Gable Roof Shed Notes

Steelwork

- 1.S All structural steelwork shall have a corrosion protection system applied consistent with AS/NZS 2312-2002.
- 2.S All structural steelwork detailed within this installation manual shall be minimum Grade 550 for roll formed sections (including roof and wall sheeting and portal frame members) and Grade 250 for angle sections.
- 3.S All multi purpose and anchor brackets for connection onto the supporting reinforced concrete slab (includes 45x45x3EA x 34mm long and 47x47x1.9EA x 80 long) shall be minimum Grade 450.
- 4.S All portal frame knee and apex plates shall be minimum Grade 450
- 5.S All roof, and wall sheeting shall be minimum base metal thickness of 0.3mm
- 6.S All portal frame members shall be minimum base metal thickness of 0.75mm.
- 7.S All snaptite channels and jambs shall be minimum base metal thickness of 0.42mm
- 8.S All top hats shall be minimum base metal thickness of 1.0mm
- 9.S All portal frame knee and apex plates shall be minimum base metal thickness 1.0mm
- 10.S All screw fasteners shall be Phil Pan Head Zinc Plated #8 x 3/4" (STP0820)
- 11.S All bolt fasteners for anchoring shall be M10 minimum grade 4.6/S
- 12.S Installation of screw fasteners shall generally be undertaken in accordance with the relevant provisions of AS1562.

Absco Industries Assembly Instruction Manual Model: 3060UTK 29/11/2021 1.3 54




3.00mW x 5.96mD x 2.10mH

Absco Large Gable Roof Shed Notes

Supporting Slab and Foundations

- 1.F The supporting slab foundation for the garden shed shall be of a minimum size indicated on the installation manual. The top surface of the formed slab shall be level and free of any irregularities which would inhibit the installation of the shed.
- 2.F The structural engineering design for the supporting slab foundation shall be undertaken by a suitably qualified structural engineer. The design shall consider all relevant provisions of AS3600 and AS2870.
- 3.F Between adjacent footings or excavations, the contractor installing the slab foundation shall not exceed a rise of 1 in a run of 2 in line of slope.
- 4.F Unless approved in writing by the slab foundation engineer, the limits of excavations near existing footings shall be in accordance with that indicated below.



The contactor shall undertake investigatory localised excavations near existing footings to ascertain their depth prior to excavating adjacent to them. It is noted that excavating to a depth below that indicated above shall not be undertaken without the written approval from the engineer.

Absco Industries Assembly Instruction Manual Model: 3060UTK 29/11/2021 1.3 55




3.00mW x 5.96mD x 2.10mH

Absco Sheds Storage Guidelines


- Absco Sheds are designed to be weatherproof for normal weather conditions. In the event of extreme weather conditions such as heavy rain, combined with high wind gusts, the ridge capping, sheeting joins, screw fixings etc., may exhibit minor deformations which may allow some water entry. These areas should be checked regularly to ensure that maximum strength and protection is maintained.
- Other weather conditions such as extreme heat and extreme cold, moist or dry air can influence the effects of concrete floor moisture and/or condensation on the underside of the roof sheets.
- Absco Sheds and storage units are primarily used for storage of garden equipment such as lawnmowers, wheelbarrows, garden tools etc. Storage items that might be adversely affected by any of the above conditions may require additional protection such as being sealed or covered by plastic sheets and/or stacked above the concrete floor on timber slats.
- Waterproof sealants may be used to offer further protection where required around joins and screw fixings, as can rubber door seals and other products which are available from most hardware outlets.
- Placement of waterproof sealants (silicone) between the base of the shed and concrete slab is not recommended, as this process can have a reverse effect, preventing excess water from escaping, resulting with water accumulating and being trapped inside the shed.
- Absco accepts no responsibility for water entry, floor moisture, condensation or the condition of the Contents inside your Absco steel building arising from any of the pre-mentioned weather conditions.



6-12 Activity St, Acacia Ridge QLD 4110 PO Box 119, Acacia Ridge QLD 4110



Model: 3060UTK



1.3

56

Lifetime Warranty Statement



This warranty against defects is given by:

Absco Industries (ABN: 77 869 708 678) Address: PO Box 119 Acacia Ridge QLD 4110

Ph: 1800 029 701 Fax: 07 3344 1191

Email: admin@absco.com.au

Date of issue: 19 December 2018

Details of Manufacturer's Warranty

This product comes with a Lifetime structural warranty from the date of purchase. This warranty also applies where there are missing or damaged parts identified in the parts list referred to in the instruction kit within the product packaging.

Please ensure that you keep this warranty form in a safe place along with your proof of purchase. You can register your warranty online http://abscosheds.com.au/warranty-details/ or complete the form on the back of this document and mail it back to Absco, along with a copy of your proof of purchase.

The benefits of this warranty are in addition to your rights under the Australian Consumer Law (ACL) and in particular, the guarantees implied under the ACL and any other rights and remedies of the consumer under a similar law in relation to the goods and services to which this warranty relates.

Process of claiming warranty:

To make a claim under the warranty within the warranty period, you will need to contact the manufacturer directly by phone or email:

Contact Number: 1800 029 701 Contact Email: admin@absco.com.au

You will be required to produce proof of purchase (this is at discretion of the manufacturer) at the time of the claim.

The manufacturer bears the cost of replacing the products or spare parts or repairing the products and reasonable direct expenses of claiming under this warranty:

Where parts are replaced, the manufacturer will bear the cost of sending the spare part and will endeavour to deliver it to the customer's nearest reseller within 20 working days for the customer to pick up. At such time the customer may be required to return the alleged faulty parts.

Where assessment is required in case of replacing or repairing the product, the manufacturer will appoint an assessor within 10 working days to identify the alleged defect. The manufacturer will bear the repair costs by appointing a local tradesman. The manufacturer may choose to replace the product if the repair or the cost of repair is not feasible. The replacement product will be available for collection from the nearest reseller within 20 working days. The customer will bear the cost of assembly for the replacement product.

IMPORTANT

1. Manufacturer's Disclosure

This warranty against defects shall not apply in the following situations:

A)Where the product is not assembled in accordance with the instructions provided in the product kit;

B)Where the product is used to store corrosive materials such as fertilizer, chlorine etc;

C)The warranty does NOT cover damage caused by storms, wind, rain, snow or poor foundations;

D)This warranty does not apply to surface deterioration of panels caused by 'Swarf' (Tiny particles of steel debris left from cutting, grinding or drilling operations) that has not been removed after building construction.

2. Notes

This product is weatherproof to a certain level; however driving windy rain may cause the product to leak. Condensation may also occur in some weather conditions such as extreme heat or cold. The product should only be used for storing items such as gardening equipment and should not be used for articles that may be prone to damage if they come into contact with moisture.

3. Major Defects

If the manufacturer is satisfied that the defect is a major defect, the purchase price may be refunded in lieu of providing a replacement product or repairing the product.

This warranty is provided in addition to other rights and remedies you have under law: Our goods come with guarantees which cannot be excluded under the Australian Consumer Law. You are entitled to replacement or refund for a major failure and to compensation for other reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.

If you do not wish to register your warranty online, complete the below form and email, fax or post this form back to Absco, along with a copy of your proof of purchase.

NAME:		
STREET ADDRESS:	POSTAL / ZIP CODE:	
STATE / CITY / PROVINCE / REGION:		
COUNTRY:		
SHED TYPE/CODE:		
ORDER NO:		
DATE OF PURCHASE:		
EMAIL ADDRESS:		
DATE REGISTERED:		